



Pinout:

- 1: GA-1000 +5V (far left terminal)
- 2: GA-1000 Green LED
- 3: GA-1000 Yellow LED
- 4: GA-1000 Red LED
- 5: CU J7 Pin 11 OR connect to same ground block as CU
- 6: CU or DU switched input (for green LED)
- 7: CU or DU switched input (for yellow LED)
- 8: CU or DU switched input (for red LED)
- 9-15: NO CONNECT

DB-15 Female J1 8 See Pin Number markings on connector.

Mounting: Can be mounted behind panel or in wingtip near the Gretz controller



317 Commercial St. NE Ste. G102
Albuquerque, NM 87102
505-241-9224

Title: GA-1000 Interface	Desc.: Interface between GA-1000 and VP-200
Designed by: Jake Dostal	Document No: 0001
Checked by: Jake Dostal	Date: 7/21/08
Approved by: Jake Dostal	Revision: 003
	Size: B
	Sheet 1 of 1